



Source Four® Fresnel

User Manual

Part Number: 7064M1200 Rev: B
Released: 2018-08

ETC® and Source Four® are registered trademarks of Electronic Theatre Controls, Inc. in the United States and other countries.

All other trademarks, both marked and not marked, are the property of their respective owners.

ETC intends this document, whether printed or electronic, to be provided in its entirety. This product is intended for professional use only. Read this entire document before using this product.

Table of Contents

Basic Assembly	1
Lamp Information	2
HPL Lamp Table	2
Installing and Replacing the Lamp	3
Adjusting the Field Angle	5
Using Accessories	6
Adjusting the Yoke	8
Adjusting the Yoke Balance Point	8
Adjusting the Fixture Angle	8
Replacing the Lens	9
Removing the lens	9
Installing the lens	10
Cleaning the Glass Lens and Reflector	10

Basic Assembly




Figure 1: Source Four Fresnel fixture components



WARNING: Please note the following safety warnings before use:

- Do not use this fixture with a damaged power lead. If the power lead (cordset) is damaged, it must be replaced.
- Do not mount the fixture on or near combustible surfaces.
- Do not operate the fixture without a lens installed.
- Always hang the fixture with the accessory holder door in the locked position.

Lamp Information

HPL Lamp Table



CAUTION: *Do not use lamps other than the HPL in Source Four fixtures. Use of lamps other than HPL will void UL/cUL safety compliance and your warranty.*

Lamp Code	Watts	Volts	Initial Lumens	Color Temp.	Average Rated Life
HPL 550/77*	550	77	16,170	3,250 K	300 hours
HPL 550/77X*	550	77	12,160	3,050 K	2000 hours
HPL 750/115	750	115	21,900	3,250 K	300 hours
HPL 750/115X	750	115	16,400	3,050 K	1500 hours
HPL 575/115	575	115	16,520	3,250 K	300 hours
HPL 575/115X	575	115	12,360	3,050 K	2000 hours
HPL 375/115	375	115	10,540	3,250 K	300 hours
HPL 375/115X	375	115	8,000	3,050 K	1000 hours
HPL 750/120	750	120	21,900	3,250 K	300 hours
HPL 750/120X	750	130	16,400	3,050 K	1500 hours
HPL 575/120	575	120	16,520	3,250 K	300 hours
HPL 575/120X	575	120	12,360	3,050 K	2000 hours
HPL 750/230	750	230	19,750	3,200 K	300 hours
HPL 750/230X	750	230	15,600	3,050 K	1500 hours
HPL 575/230	575	230	14,900	3,200 K	400 hours
HPL 575/230X	575	230	11,780	3,050 K	1500 hours
HPL 375/230X	375	230	7,250	3,000 K	1000 hours
HPL 750/240	750	240	19,750	3,200 K	300 hours
HPL 750/240X	750	240	15,600	3,050 K	1500 hours
HPL 575/240	575	240	14,900	3,050 K	400 hours
HPL 575/240X	575	240	11,780	3,050 K	1500 hours
HPL 375/240X	375	240	7,250	3,000 K	1000 hours
* To be used with ETC Dimmer Doubler™					

Installing and Replacing the Lamp

A lamp must be installed before you use the fixture.




Figure 2: Lamp door on bottom of the fixture



Note: Verify that the HPL lamp you intend to install is suitable for your facility's voltage; 115V, 120V, 230V, and 240V HPL lamps are available. See [HPL Lamp Table](#) on [page 2](#). Operating HPL lamps above their rated voltage reduces lamp life and can cause premature lamp failure.



WARNING: Unplug the fixture and allow it to cool down before changing the lamp.

- 1: Disconnect power to the fixture before installing or replacing the lamp.
- 2: On the bottom of the fixture, turn the latch on the lamp door one quarter-turn and then open the door.
- 3: Remove the lamp holder assembly by turning the knurled knob counterclockwise to release the lamp socket assembly.
- 4: Twist the lamp socket assembly counterclockwise one quarter-turn and remove from the fixture.



CAUTION: The socket assembly remains connected to the fixture by means of its electrical leads. Do not pull the wired assembly or place undue stress on it.




Figure 3: Remove lamp with quarter-turn counterclockwise


- 5: If replacing a lamp, carefully remove the old lamp from the lamp socket assembly.
- 6: Holding the new HPL lamp by the base, remove it from its box.



CAUTION: *Use caution when installing or replacing any lamp.*

When installing and replacing lamp, be sure to point the lamp away from your face and away from others before inserting it firmly into the assembly. This may prevent injuries if the lamp should break.

CORRECT



INCORRECT



Note: *To avoid premature lamp failure, do not touch the lamp glass. If you do, clean it carefully with isopropyl alcohol and a clean lint-free cloth. Allow to dry before operation.*

- 7: Align the flat sides of the lamp base with the retention brackets on either side of the socket in the lamp holder assembly as shown in [Figure 3](#).
- 8: Push down on the lamp base until the lamp seats firmly. When properly installed, the top of the lamp's base will be even with the top edges of the retention brackets.



CAUTION: *Improperly installed lamps and lamp holder assemblies can cause premature lamp failure and socket problems.*

- 9: Reinstall the lamp holder assembly into its socket in the fixture so that the arrow points towards the "unlock" icon on the socket.
- 10: Turn the lamp holder assembly clockwise one quarter-turn so that the arrow points to the "lock" icon.
- 11: Turn the knurled knob clockwise to secure the lamp holder assembly.
- 12: Close the lamp housing door and turn the latch to secure the door.

Adjusting the Field Angle

You can adjust the field angle of the fixture from 20° to 65° with the field angle adjustment knob.

- 1: Lift the locking lever to unlock the field angle adjustment knob.






Figure 4: Field angle adjustment knob and locking lever



CAUTION: *The field angle adjustment knob does not rotate 360°. Do not attempt to exceed the rotation limit.*

- 2: Do one of the following:
 - To reduce the field angle, turn the field angle adjustment knob counterclockwise.
 - To enlarge the field angle, turn the field angle adjustment knob clockwise.

Field angle
adjustment
knob in flood
position



Field angle
adjustment
knob in spot
position





Figure 5: Field adjustment from flood to spot

- 3: To lock the field angle adjustment knob, press the locking lever into place.

Using Accessories

The accessory holder is equipped with two slots and a locking door that prevents color frames and accessories from falling out.




Figure 6: Accessory holder door in the open position



WARNING: Make sure all color frames and accessories are locked in position with the accessory door before hanging the fixture.

Accessories such as barn doors and color scrollers must be secured with safety cables to the mounting position, such as batten, truss, or other secure structure.

Fixture should never be oriented so that the weight of the accessories, such as color scrollers or barn doors, rests against the accessory holder door.




Figure 7: Fixture with accessories

- 1: Release the accessory holder door by turning the fastener one quarter-turn counterclockwise and lifting the front of the door.




Figure 8: Accessory holder door releases

- 2: Insert the color frame or accessory.
- 3: Close the accessory door, and then press and turn the fastener one quarter-turn clockwise to lock the door in place.



Note: Use only color frames or accessories with a 7.5 inch mounting flange.



Note: The performance of saturated colors may be less than desirable in any theatrical lighting fixture, especially when equipped with a 750W lamp. For best results, always use high-quality color media rated for high-temperature use.

A variety of heat shield products is also available from many color media manufacturers. Follow the manufacturer's instructions for the use of these products.

Adjusting the Yoke

Adjusting the Yoke Balance Point

You can adjust the yoke mounting position on the fixture to accommodate varying weights of different accessories. For example, move the yoke balance point forward (toward the lens) to balance the additional weight of a color scroller and barn door assembly in the accessory slot.

- 1: Loosen the nuts on both sides of the yoke assembly while keeping the fixture steady using the handle on the rear of the unit.




Figure 9: Yoke balance and angle adjustment

- 2: Loosen the yoke locking knob so that the fixture moves freely.
- 3: Slide the fixture back and forth until it is properly balanced.
- 4: Tighten the yoke locking knob.
- 5: Tighten the two nuts.

Adjusting the Fixture Angle

You can tilt the fixture up and down to position the light where it is needed. See [Figure 9](#).

- 1: On the side of the yoke, loosen the yoke locking knob while keeping the fixture steady using the handle on the rear of the unit.
- 2: With the fixture turned on, use the handle to tilt the fixture to the desired angle.
- 3: Tighten the yoke locking knob.

Replacing the Lens

Replace the lens if it becomes cracked or badly scratched.



CAUTION: *Never operate the fixture without a lens in place.*



WARNING: **Unplug the fixture and allow it to cool down before changing a lens.**

Removing the lens

- 1: Place the fixture on a flat, stable work surface. **Do not** remove or install the lens when the fixture is hanging.
- 2: Tilt the front of the fixture down at least 45°.
- 3: Use a flat-blade screwdriver to slide the two plastic lens retaining clips on each side of the lens outward to release the lens.




Figure 10: Lens retaining clip

- 4: Allow the top of the lens to drop forward from under the clips while using your hand to prevent the lens from falling.




Figure 11: Removing the lens

- 5: Carefully remove the lens.

Installing the lens



Note: *Do not leave fingerprints on the lens. Handle the lens with a soft, clean cloth.*

- 1: Position the fixture with the front of the unit (lens side) facing you, and tilted slightly upward.
 - 2: Hold the lens by the edge and position it so the stepped side faces the front of the fixture.
-



Note: *The lens will not fit properly and will not function correctly if it is installed with the stepped side facing the rear of the fixture.*

- 3: From the top of the fixture, slide the lens into the lens retaining slot and then rotate the top of the lens into place.
 - 4: Slide the plastic lens retaining clips on each side of the lens inward to secure the lens. See [Figure 10](#).
-

Cleaning the Glass Lens and Reflector



WARNING: Do not use ammonia-based or other harsh commercial cleaners. Clean lens only as directed.

Commercially available glass cleaning agents should be avoided because they may contain ammonia, other harsh chemical detergents, or abrasive agents. These cleaners may damage the glass surface and the Anti-Reflective coatings. Do not immerse or soak the glass in any cleaning solution.

Replace the lens if it contains visible damage such as cracks or deep scratches that may impair its effectiveness.

The reflector is located behind the lamp. You must remove the lamp before cleaning the reflector.

Remove dust with a blast of oil-free air or wipe with a clean, lint-free cloth. You can use isopropyl alcohol, distilled water, or a 50%–50% mixture of both to clean the lens and reflector.



Corporate Headquarters ■ Middleton, WI, USA ■ Tel +608 831 4116 ■ Service: (Americas) service@etcconnect.com
London, UK ■ Tel +44 (0)20 8896 1000 ■ Service: (UK) service@etceurope.com
Rome, IT ■ Tel +39 (06) 32 111 683 ■ Service: (UK) service@etceurope.com
Holzkirchen, DE ■ Tel +49 (80 24) 47 00-0 ■ Service: (DE) techserv-hoki@etcconnect.com
Hong Kong ■ Tel +852 2799 1220 ■ Service: (Asia) service@etcasia.com
Web: etcconnect.com ■ © 2018 Electronic Theatre Controls, Inc.

Product information and specifications subject to change. ETC intends this document to be provided in its entirety.
7046M1200 ■ Rev B ■ Released 2018-08