



# PRECEPT 36 MICROCOMPUTER LIGHTING DESK





### THE PRECEPT 36

- 36 Output Channels.
- 2 banks of presets. Lower preset group can operate as Scene Masters.
- 144 level conscious programmable scenes.
- Full Edit facility on all recorded scenes.
- 36 programmable chase sequences of up to 99 steps each.
- Masters for upper and lower preset.
- Independent Master to which a scene or channel can be assigned.
- Upper and lower preset masters can be used as auxiliary Independent Masters.
- Master for Chase Intensity.
- Master for Chase Speed.
- Reverse button for chase.
- Single step button for chase.
- Solo buttons for each channel.
- Solo buttons for each scene.
- Solo buttons for each master.
- Add and Kill on all solos.
- Add master for solo buttons.
- Kill master for solo buttons.
- Preview Function to cue scenes and chasers.
- Blind programming of scenes and chasers.
- External triggering function.
- Restrict function.
- Output level LED display.
- Battery backed up memory.
- External memory storage facility.
- Control cable is a single 5 core cable with demultiplexer (if required) sited at the dimmer racks.

### Output:

RS485 Digital Communications Link. Complies with USITT DMX512.

### Output Connection:

Female 5 pin 'XLR' style microphone connector.

### Analog Conversion:

Via L.S.C. LINKLIGHT Multiplexer.

### Power Requirements:

The PRECEPT 36 is supplied with an external 8.8 Volt AC Plug-pack power supply.

### Dimensions:

70mm x 1440mm x 420mm overall.

### Construction:

Mild sheet steel finished in black baked enamel. End pieces are polished hard wood.

### Weight:

18 kg.

### Avolites Production Company Limited

184 Park Avenue London NW107XL.

Telephone (01) 965 8522 Telex 24652 Spoton G. Facsimile (01) 965 0291

### Avolites Inc.

9700 Owensmouth Avenue Unit B Chatsworth CA 91311.

Telephone (818) 709 1116. Telex 705035 Avolites. Facsimile (818) 709 0153

---

Avolites reserves the right to alter any specification without prior notice.